



TP70/P5 Protocol for ICT002 / Pulse

COP5 Support bill 2000 、 5000 、 10000 、 20000 、 50000 (Colombia)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / COP 1000	OFF	OFF	OFF							
	2 Pulse / COP 1000	OFF	OFF	ON							
	3 Pulse / COP 1000	OFF	ON	OFF							
	4 Pulse / COP 1000	OFF	ON	ON							
	5 Pulse / COP 1000	ON	OFF	OFF							
	10 Pulse / COP 1000	ON	OFF	ON							
	20 Pulse / COP 1000	ON	ON	OFF							
	100 Pulse / COP 1000	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept COP 2000						ON				
	Reject COP 2000						OFF				
★	Accept COP 5000							ON			
	Reject COP 5000							OFF			
★	Accept COP 10000								ON		
	Reject COP 10000								OFF		
★	Accept COP 20000									ON	
	Reject COP 20000									OFF	
★	Accept COP 50000										ON
	Reject COP 50000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

DIP SW SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Straight			ON	
★	Turn Over			OFF	
	Ignore Sensor Problem (Note 1)				ON
★	Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note: (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be Flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.

(The face LED will be flashing in red.)