



## TP70/P5 Protocol for ICT106 / Pulse

**VND6 Support bill 10000, 20000, 50000, 100000, 200000, 500000 (Vietnam)**

### DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / VND 10000	OFF	OFF	OFF							
	2 Pulse / VND 10000	OFF	OFF	ON							
	3 Pulse / VND 10000	OFF	ON	OFF							
	4 Pulse / VND 10000	OFF	ON	ON							
	5 Pulse / VND 10000	ON	OFF	OFF							
	10 Pulse / VND 10000	ON	OFF	ON							
	20 Pulse / VND 10000	ON	ON	OFF							
	100 Pulse / VND 10000	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept VND 10,000 / 20,000				ON						
	Reject VND 10,000 / 20,000				OFF						
★	Accept VND 50,000				ON						
	Reject VND 50,000				OFF						
★	Accept VND 100,000				ON						
	Reject VND 100,000				OFF						
★	Accept VND 200,000				ON						
	Reject VND 200,000				OFF						
★	Accept VND 500,000				ON						
	Reject VND 500,000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

### DIP SW SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Straight			ON	
★	Turn Over			OFF	
	Ignore Sensor Problem (Note 1)				ON
★	Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note: (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be Flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.

(The face LED will be flashing in red.)