



## TP70/P5 Protocol for ICT002 / Pulse

**ZAR5 Support bill 10、 20、 50、 100、 200 (SouthAfrican)**

### DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / ZAR 10	OFF	OFF	OFF							
	2 Pulse / ZAR 10	OFF	OFF	ON							
	3 Pulse / ZAR 10	OFF	ON	OFF							
	4 Pulse / ZAR 10	OFF	ON	ON							
	5 Pulse / ZAR 10	ON	OFF	OFF							
	10 Pulse / ZAR 10	ON	OFF	ON							
	20 Pulse / ZAR 10	ON	ON	OFF							
	100 Pulse / ZAR 10	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept ZAR 10						ON				
	Reject ZAR 10						OFF				
★	Accept ZAR 20							ON			
	Reject ZAR 20							OFF			
★	Accept ZAR 50								ON		
	Reject ZAR 50								OFF		
★	Accept ZAR 100									ON	
	Reject ZAR 100									OFF	
★	Accept ZAR 200										ON
	Reject ZAR 200										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

### DIP SW SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Straight			ON	
★	Turn Over			OFF	
	Manufacture				ON
★	System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switches 1 are used for pulse protocol.