



TP77/P5 Protocol for ICT002 / Pulse

SCR3 Support bill 10, 25, 50 (Seychelles)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / SCR 5	OFF	OFF	OFF							
	2 Pulse / SCR 5	OFF	OFF	ON							
	3 Pulse / SCR 5	OFF	ON	OFF							
	4 Pulse / SCR 5	OFF	ON	ON							
	5 Pulse / SCR 5	ON	OFF	OFF							
	10 Pulse / SCR 5	ON	OFF	ON							
	20 Pulse / SCR 5	ON	ON	OFF							
	100 Pulse / SCR 5	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept SCR 10				ON						
	Reject SCR 10				OFF						
★	Accept SCR 25				ON						
	Reject SCR 25				OFF						
★	Accept SCR 50				ON						
	Reject SCR 50				OFF						
★	Reserved				ON						
	Reserved				OFF						
★	Reserved				ON						
	Reserved				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

DIP SW SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High (NO)	ON			
Pulse Normal Low (NC)	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
Straight			ON	
★ Turn Over			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch